


Line A-Technical Reference  
Manual

Sept. 9, 1985

ATARI CORP. CONFIDENTIAL  
Sept. 9, 1985



LINE A-DOCUMENT  
TABLE OF CONTENTS

Initialization.....	1
Put pixel.....	1
Get pixel.....	1
Line.....	1
Horizontal line.....	1
Filled rectangle.....	1
Line-by-line filled polygon.....	1
BitBlt.....	1
TextBlt.....	1
Show mouse.....	1
Hide mouse.....	1
Transform mouse.....	1
Undraw sprite.....	1
Draw sprite.....	1
Copy raster form.....	1
Seedfill. (exists only in versions of TOS after the 1st release).....	1
(0) Initialization.....	1
(1) Put pixel.....	2
(2) Get pixel.....	3
(3) Line.....	3
(4) Horizontal line.....	4
(5) Filled rectangle.....	4
(6) Line-by-line filled polygon.....	5
(7) BitBlt.....	5

BIT BLT PARAMETER BLOCK OFFSETS.....	6
0. PREFACE.....	7
I. PARAMETER BLOCK.....	7
II. MEMORY FORMS.....	8
III. RASTER OPERATIONS.....	9
IV. PATTERNS.....	9
V. BAG 'O TRICKS.....	10
(8)            TextBlt.....	12
(9)            Show mouse.....	13
(10)           Hide mouse.....	13
(11)           Transform mouse.....	13
(12)           Undraw sprite.....	13
(13)           Draw sprite.....	14
(14)           Copy raster form.....	15
USING THE LINE "A" INTERFACE.....	15
The LINE"A" input variables structure:.....	15

## THE LONG-AWAITED LINE "A" DOCUMENT

In order to provide "quick-and-dirty" access to the assembler-level graphics routines, ATARI engineers have set up the 68000's LINE "A" exception as an interface to several useful routines. The LINE "A" interface is faster than going through GEM's VDI and has some extra features. Also, LINE "A" calls require less application code than their VDI counterparts. Of course, LINE "A" doesn't replace the VDI completely, but if an application only needs a few primitive graphics functions (and wants maximum performance), then LINE "A" is sufficient (and optimal).

The LINE "A" interface is provided for the hacker-at-heart and no claims are made about its ease of use. The interface may seem unusually inconsistent, but it was not designed; it simply fell out as a freebie from the low-level VDI primitives interface. That is, these routines are the heart of the VDI.

The LINE "A" interface consists of 15 opcodes. The calls to LINE "A" are assembled as 1-word instructions, the highest 4 bits of which are 1010 (A in hexadecimal, hence LINE "A") and the lower 12 bits of which are used as the opcode field. Following is a description of the 15 opcodes:

- 0 = Initialization.
- 1 = Put pixel.
- 2 = Get pixel.
- 3 = Line.
- 4 = Horizontal line.
- 5 = Filled rectangle.
- 6 = Line-by-line filled polygon.
- 7 = BitBlt.
- 8 = TextBlt.
- 9 = Show mouse.
- 10 = Hide mouse.
- 11 = Transform mouse.
- 12 = Undraw sprite.
- 13 = Draw sprite.
- 14 = Copy raster form.
- 15 = Seedfill. (exists only in versions of TOS after the 1st release)

The LINE "A" routines have some features that the VDI doesn't support. BitBlt supports half-tone patterns on the source and TextBlt supports all 16 BitBlt logic operations, not just the 4 GEM VDI writing modes. In addition to these straight-forward extensions LINE "A" also allows the adventurous programmer to experiment with special effects. The BitBlt is especially generous in this area.

(0) Initialization

```
*** ***
dc.w $A000          ; Init the LINE "A".
*** ***
```

input: none.

output: d0 = ptr to the base address of LINE "A" interface variables.

a0 = ptr to the base address of LINE "A" interface variables.

a1 = ptr to array of ptrs to the 3 system font headers.

a2 = ptr to array of ptrs to the 15 LINE "A" routines.

note: The value returned in a0 is the sine qua non of the LINE "A" interface. Inputs to all the other LINE "A" operations are made relative to this value, i.e., the LINE "A" interface variables are contained in a structure pointed to by a0. The offsets of these variables in the structure are given below.

bugs: In the first TOS release, a2 is not returned as described above. Instead, it is preserved across the LINE "A" call. See Example Program #2 at the end of this document for the technique that makes a2 point to the proper place.

#### (1) Put pixel

```
*** ***
dc.w $A001          ; Plot a pixel at x,y.
*** ***
```

input: INTIN[0] = pixel value.  
PTSIN[0] = x coordinate.  
PTSIN[1] = y coordinate.

output: none.

note: For a discussion of the CONTRL, INTIN, PTSIN, INTOUT, & PTSOUT arrays, see the GEM VDI manual.

(2) Get pixel

```
... ..  
dc.w #A002 ; Get the pixel at x,y.  
... ..
```

input: PTSIN[0] = x coordinate.  
PTSIN[1] = y coordinate.

output: d0 = pixel value.

(3) Line

```
... ..  
dc.w #A003 ; Draw a line between (x1,y1) and  
... .. (x2,y2).
```

input: X1 = x1 coordinate.  
Y1 = y1 coordinate.  
X2 = x2 coordinate.  
Y2 = y2 coordinate.  
COLBIT0 = bit value for plane 0.  
COLBIT1 = bit value for plane 1.  
COLBIT2 = bit value for plane 2.  
COLBIT3 = bit value for plane 3.  
LNMASK = line style mask.  
WMODE = writing mode.  
LSTLIN = always set this to -1, if using  
xor mode else ignore it.

output: LNMASK is rotated to align with right-most  
endpoint.

quirks: 1) If the line is horizontal, LNMASK is a  
word-aligned pattern, not a line style. That  
is, a bit other than bit 15 of LNMASK may be  
used at the left-most endpoint.  
2) As the foregoing references imply, the line  
is always drawn from left to right, not from  
(X1,Y1) to (X2,Y2). Thus, LNMASK is always  
applied from left to right.

note: Because of the quirks, an application cannot  
depend upon the phase of the LNMASK being  
properly updated between calls to line-drawing  
primitives. If the phase is critical, the  
application must compute and init LNMASK  
before each line is drawn.

LNMASK is applied to the line-drawing DDA algorithm along the direction of greater delta. If delta Y is greater than delta X, then LNMASK is applied in the Y direction.

These line-drawing quirks and notes apply to the GEM VDI, too.

(4) Horizontal line

```
... ..  
dc.w $A004          ; Draw a line from (x1,y1) to  
                   (x2,y1).  
... ..
```

```
input:             X1 = x1 coordinate.  
                  Y1 = y1 coordinate.  
                  X2 = x2 coordinate.  
                  COLBIT0 = bit value for plane 0.  
                  COLBIT1 = bit value for plane 1.  
                  COLBIT2 = bit value for plane 2.  
                  COLBIT3 = bit value for plane 3.  
                  WMODE  = writing mode.  
                  PATPTR = ptr to the fill pattern.  
                  PATMSK = pattern index.  
                  MFILL  = multi-plane pattern flag.
```

```
output:           none.
```

(5) Filled rectangle

```
... ..  
dc.w $A005          ; Draw a filled rectangle with upper left  
                   ; corner at (x1,y1) and lower right corner at  
                   ; (x2,y2).  
... ..
```

```
input:             X1 = x1 coordinate.  
                  Y1 = y1 coordinate.  
                  X2 = x2 coordinate.  
                  Y2 = y2 coordinate.  
                  COLBIT0 = bit value for plane 0.  
                  COLBIT1 = bit value for plane 1.  
                  COLBIT2 = bit value for plane 2.  
                  COLBIT3 = bit value for plane 3.  
                  WMODE  = writing mode.  
                  PATPTR = ptr to the fill pattern.  
                  PATMSK = fill pattern index.  
                  MFILL  = multi-plane fill pattern flag.  
                  CLIP  = clipping flag.  
                  XMINCL = x minimum for clipping.
```



XMAXCL = x maximum for clipping.  
YMINCL = y minimum for clipping.  
YMAXCL = y maximum for clipping.

output: none.

(6) Line-by-line filled polygon.

... ..  
dc.w \$A006 ; Draw 1 scan-line of a filled polygon.  
... ..

input: PTSIN[] = array of polygon vertices.  
(x1,y1),(x2,y2)...,(xn,yn),(x1,y1)  
CONTRL[] = n = number of vertices.  
Y1 = y coordinate of scan-line to fill.  
COLBIT0 = bit value for plane 0.  
COLBIT1 = bit value for plane 1.  
COLBIT2 = bit value for plane 2.  
COLBIT3 = bit value for plane 3.  
WMODE = writing mode.  
PATPTR = ptr to the fill pattern.  
PATMSK = fill pattern mask.  
MFILL = multi-plane fill pattern flag.  
CLIP = clipping flag.  
XMINCL = x minimum for clipping.  
XMAXCL = x maximum for clipping.  
YMINCL = y minimum for clipping.  
YMAXCL = y maximum for clipping.

output: X1 and X2 are clobbered.

note: The 1st endpoint must be repeated at the end  
of the list of n endpoints.

(7) BitBlit

... ..  
dc.w \$A007 ; Perform a BIT BLock Transfer.  
... ..

input: a6 = ptr to a structure of input parameters.

output: none.

BIT BLT PARAMETER BLOCK OFFSETS

B_WD	equ	+00	; width of block in pixels
B_HT	equ	+02	; height of block in pixels
PLANE_CT	equ	+04	; number of consecutive planes to blt (D)
FG_COL	equ	+06	; foreground color (logic op index:hi bit) (D)
BG_COL	equ	+08	; background color (logic op index:lo bit) (D)
OP_TAB	equ	+10	; logic ops for all fore and background combos
S_XMIN	equ	+14	; minimum X: source
S_YMIN	equ	+16	; minimum Y: source
S_FORM	equ	+18	; source form base address
S_NXWD	equ	+22	; offset to next word in line (in bytes)
S_NXLN	equ	+24	; offset to next line in plane (in bytes)
S_NXPL	equ	+26	; offset to next plane from start of current plane
D_XMIN	equ	+28	; minimum X: destination
D_YMIN	equ	+30	; minimum Y: destination
D_FORM	equ	+32	; destination form base address
D_NXWD	equ	+36	; offset to next word in line (in bytes)
D_NXLN	equ	+38	; offset to next line in plane (in bytes)
D_NXPL	equ	+40	; offset to next plane from start of current plane
P_ADDR	equ	+42	; address of pattern buffer (0:no pattern) (D)
P_NXLN	equ	+46	; offset to next line in pattern (in bytes)
P_NXPL	equ	+48	; offset to next plane in pattern (in bytes)
P_MASK	equ	+50	; pattern index mask
P_BLOCK_LEN	equ	76	; the parameter block must be 76 bytes long

\*\*\* notes \*\*\*

parameters marked with (D) may be altered during the course of the BIT BLT execution

## contents of OP\_TAB

- +00 byte logic operation employed when foreground and background color bits for current plane are both clear (0)
- +01 byte logic operation employed when current plane's foreground color bit is clear (0) and background color bit is set (1)
- +02 byte logic operation employed when current plane's foreground color bit is set (1) and background color bit is clear (0)
- +03 byte logic operation employed when foreground and background color bits for current plane are both set (1)

## 0. PREFACE

Before one floggles one's tormented mind with this tangled nest of arcane knowledge, one ought to be intimately familiar with chapter 6 of the GEM VDI manual. the author assumes that one's knowledge of Raster matters is quite wide and that the rudiments of BIT BLTING are below discussion. If the author is mistaken then he's sorry (and you're about to become lost in the sea of woe, oh ho!).

## 1. PARAMETER BLOCK

The BIT BLT is accessed via a 76 byte parameter block. Register A6 points to the head of this block upon LINE A entry. Only the first 52 bytes of the block need be attended to by the abuser. The remaining space is maintained internally by the BLT. Note that in the following explanations, parameters will be referred to by their symbolic offsets into the parameter block.

## II. MEMORY FORMS

Memory forms are something like a cabbage patch. (a cabbage patch is a place for mentally retarded programmers). let's face it, forms are nothing like a cabbage patch. if you think they are, go back and read chapter 6 in the GEM VDI manual. if you know anything at all about memory forms, you know they are almost entirely but not totally unlike a garbage can. one difference is that memory forms are of two sexes, source and destination. each sex is defined by the same four parameters: form block address, form block width, offset to next contiguous word, and offset to next plane.

S\_FORM and D\_FORM point to the first words of the source memory form and destination memory forms, respectively. these addresses must fall on word boundaries or severe hardships will fall (as will address exceptions) like plagues upon the ancient egyptians.

S\_NXWD and D\_NXWD are offsets to the next word in a plane of the memory form. for example, in the monochrome mode the value is 2 while a value of 4 is used in medium resolution and 8 is applicable to low resolution.

S\_NXLN and D\_NXLN are form widths for source and destination. ( i can't remember which one belongs to the source form and which one belongs to the destination form). These widths must be even byte values, as you know, for they represent the offset from one row of the form to the next and forms must be word aligned and an integral number of words wide. (hint: the hi rez screen value is 90 while lo and medium rez values are 160)

S\_NXPL and D\_NXPL are offsets from the start of one plane to the start of the next plane. because of the ST screen's interleaved plane structure, this value is always two (2). alternative universes allow for a series of contiguous planes where NXPL values are the number of bytes in each plane. thus , it is possible to BLT from the contiguous universe into the interleaved ST universe and vice versa.

the actual bit aligned blocks of memory are defined within the form by an upper left anchor point, a pixel width, and a pixel height: (S\_XMIN, S\_YMIN, B\_WD, and B\_HT). the location in the destination form is defined by an anchor point (D\_XMIN, D\_YMIN). no harm will come if these two areas overlap. Note that no clipping is performed and there is no checking to determine whether the bit blocks fall within the confines of the encompassing memory forms. finally, the number of planes to be transferred (the number of iterations of the BLT algorithm) is contained in the PLANE\_CT word.

### III. RASTER OPERATIONS

OP\_TAB is a table of four RASTER OP codes. Each of the byte wide entries in OP\_TAB contain a code for one of the sixteen logical operations between consenting source and destination blocks. For each plane, the logical operation is chosen by indexing into the OP\_TAB with a value derived from FG\_COL and BG\_COL words. For a given plane "n", bit "n" of FG\_COL is the hi bit of the two bit index value and bit "n" of BG\_COL is the lo bit of the index value.

for those with a furniture fetish, here is a table:

<u>FG(n)</u>	<u>BG(n)</u>	<u>OP_TAB entry</u>
0	0	first entry
0	1	second entry
1	0	third entry
1	1	fourth entry

### IV. PATTERNS

Patterns are word wide, word aligned images that are logically anded with the source prior to the logical combination of source with destination.

Patterns are packed in an imaginary grid anchored at the upper left corner (0,0) of the destination memory form.

Patterns are 16 bits wide and repeated every 16 pixels horizontally.

Patterns are an integral power of 2 in height and repeat vertically at that frequency.

The source is shifted into alignment with the destination rectangle prior to the combination of source with pattern. Thus, the relationship between source and pattern is dependent upon the X,Y positioning of the destination rectangle.

P\_ADDR points to the first word of the pattern. If this pointer is 0, a pattern is not combined with the source rectangle.

P\_NXLN is the offset (in bytes) between consecutive words in the pattern. For reasons too inane to go into here, this number should be an integral power of 2 (such as 2,4, or 8)

P\_NXPL is the offset (in bytes) from the beginning of a plane to the beginning of the next plane. In the case of a single plane pattern used in a multi-plane environment, this value would be zero. thus, the same pattern is repeated through all planes.

P\_MASK works with P\_NXLN to specify the length of the pattern. The length (in words) of the pattern must be an integral power of 2.

```
if P_NXLN = 2 ** n
then P_MASK = (length in words -1) << n
... i don't know why. go ask your father.
```

#### V. BAG 'O TRICKS

Q. I want to BLT from a single plane source to multi-plane destination.

A. That's not in the form of a question. And besides, i can't think with that water pick spurtin in my ear. Hey, that's my cat your puttin in the Cuisinart. Wha the fuh you think your doin bustin into my word processor like this. Hey bud, stay away from that delete key. Hey moe foe, i'm serious. How'd you like an unexpected interrupt ?

Q. This key is loaded and it's pointed at your bonus check.

A. ok,ok... i'll talk.

S\_NXPL =0 => the same source plane is BLTED to all destination planes

Q. yea, i know that but what logic ops do i use ?

A. to map 1's to foreground color and 0's to background color

set DF\_TAB to:

offset	logic op	
+00	00	all zeros
+01	04	D' <- [not S] and D
+02	07	D' <- S or D
+03	15	all ones

load foreground color into FG\_COL and background color into BG\_COL

Q. you wanna buy some lake bottom property?

A. to map 1's to foreground color and make 0's transparent  
set OP\_TAB to:

offset	logic op	
+00	04	D' ← [not S] and D
+01	04	D' ← [not S] and D
+02	07	D' ← S or D
+03	07	D' ← S or D

load foreground color into FG\_COL  
it doesn't matter what you put into BG\_COL

don't forget to set S\_NXPL to 0

enough smalltalk, let's get down to the core of the issue.  
Here are some of my Aunt Marge's flavorful BIT BLT recipes:

1. BLT a pattern without Source to the Destination.

For this number, we'll need a word of ones. Label it "ones:"  
next, point S\_FORM at "ones". Set S\_NXLN, S\_NXPL, S\_NXWD,  
S\_XMIN, and S\_YMIN to 0. Set up the pattern as you usually  
would and before you know it, you'll have a wonderful  
steaming pattern filled rectangle.

2. this is a nice way to make a sprite like device.

o you will need to bake a monoplane mask. everywhere there  
is a 1 in the mask, the background will be removed.  
wherever a 0 falls, the background is left intact.

set OP\_TAB to:

offset	logic op	
+00	04	D' ← [not S] and D
+01	04	D' ← [not S] and D
+02	07	D' ← S or D
+03	07	D' ← S or D

load foreground color into FG\_COL  
it doesn't matter what you put into BG\_COL

- o next, take a mono-plane form (or multi-plane form) and "or" it (OP 07) into the area that you just scooped out with the mask feeds a family of four.

(8) TextBlt

```
... ..  
dc.w $A008 ; Perform a TEXT BLock Transfer of 1  
character.  
... ..
```

input:

WMODE = writing mode. (0-3 => VDI modes.  
4-19 => BitBlt modes)

TEXTFG = text foreground color.  
TEXTBG = text background color. (used for modes 4-19)  
FBASE = ptr to start of font data. (font form)  
FWIDTH = width of font form.  
SOURCEX = x coord of character in font form.  
SOURCEY = y coord of character in font form.  
DESTX = x coord of character on screen.  
DESTY = y coord of character on screen.  
DELX = width of character.  
DELY = height of character.  
STYLE = vector of TextBlt special effects flags.  
LITEMASK = the mask to use in lightening text.  
SKEWMASK = the mask to use in skewing text.  
WEIGHT = the width by which to thicken text.  
ROFF = offset above character baseline when  
skewing.  
LOFF = offset below character baseline when  
skewing.  
SCALE = scaling flag. (0 => no scaling.)  
XDDA = accumulator for x dda.  
DDAINC = fractional amount to scale up or down.  
SCALDIR = scale direction flag. (0 => down)  
CHUP = character rotation vector.  
MONO = monospaced font flag.  
SCRTCHP = ptr to start of text special effects buffer.



SCRPT2 = offset of scaling buffer in above buffer.

output: none.

(9) Show mouse

```
... ..  
dc.w $A009 ; Show the mouse.  
... ..
```

input: see GEM VDI manual.

output: none.

(10) Hide mouse

```
... ..  
dc.w $A00A ; Hide the mouse.  
... ..
```

input: see GEM VDI manual.

output: none.

(11) Transform mouse

```
... ..  
dc.w $A00B ; Transform the mouse's form.  
... ..
```

input: see GEM VDI manual.

output: none.

(12) Undraw sprite

```
... ..  
dc.w $A00C ; Undraw the previously drawn sprite.  
... ..
```

input: a2 = ptr to sprite save block.

note: The sprite save block is used to save the screen underneath the sprite. Its size is 10 bytes + 64 bytes per plane, i.e. (10 + VPLANES \* 64) bytes.

output: clobbers a6. ("C" programmers beware.)

(13) Draw sprite

```
*** ***  
dc.w #A00D ; Draw a sprite.  
*** ***
```

```
input:      d0 = x hot-spot.  
           d1 = y hot_spot.  
           a0 = ptr to sprite definition block.  
           a2 = ptr to sprite save block.
```

#### SPRITE DEFINITION BLOCK LAYOUT

```
ds.w 1      x offset of hot-spot.  
ds.w 1      y offset of hot-spot.  
ds.w 1      format flag. (1 => VDI Format,  
                    -1 => XOR Format)
```

#### VDI Format

fg bit	bg bit	action
0	0	transparent to screen
0	1	background color plotted
1	0	foreground color plotted
1	1	foreground color plotted

#### XOR Format

fg bit	bg bit	action
0	0	transparent to screen
0	1	background color plotted
1	0	xor screen
1	1	foreground color plotted

```
ds.w 1      background color (color table  
            index)  
ds.w 1      foreground color (color table  
            index)  
ds.w 32     interleaved background/foreground  
            image.  
            (word 0 = background line 0.  
            word 1 = foreground line 0.  
            word 2 = background line 1.  
            word 3 = foreground line 1.
```

etc.)

output: clobbers a6. ("C" programmers beware.)

bugs: This function is not usable as a LINE "A" call in the 1st release of TOS. See Example Program #2 below for the technique one must adopt to use this function.

(14) Copy raster form

```
... ..  
dc.w $A00E ; Copy a raster form from source to  
destination.  
... ..
```

input: See the VDI discussion of Copy Raster, Opaque & Transparent, EXCEPT, CONTRL(0), CONTRL(1), CONTRL(3), and CONTRL(6) are ignored. COPYTRAN = Opaque/Transparent mode flag. (0 => Opaque)

output: none.

note: See the BitBlt discussion above.

#### USING THE LINE "A" INTERFACE

The inputs to the LINE "A" routines are contained in a structure pointed to by the value returned in a0 after an initialization call (\$A000) has been made. This initialization only needs to be done once and any returned values can be saved and used as needed.

The LINE "A" interface can be used in cooperation with the VDI and AES, however, one cannot expect the variables below to be unchanged after the VDI or AES has been used. Therefore, if an application wants to mix calls to LINE "A" and VDI/AES, it must reload any variables that it uses as input to the LINE "A" routines.

The caller should assume that registers d0-d2 and a0-a2 are clobbered upon return. The rest are preserved.

The LINE "A" input variables structure:

offset	name	type	description
--------	------	------	-------------

Line - A Document PAGE 15 ATARI CORP. CONFIDENTIAL

0	VPLANES	word	number of video planes.
2	VWRAP	word	number of bytes/video

line.

note: These variables can be changed to implement special effects, e.g., doubling VWRAP will cause the routines to skip 1 scanline between every scanline that is output to the screen. Of course, any modifications made to these variables must be undone when normal operation of the LINE "A" (or VDI) is desired.

4	CONTRL	long	ptr to the CONTRL array.
8	INTIN	long	ptr to the INTIN array.
12	PTSIN	long	ptr to the PTSIN array.
16	INTOUT	long	ptr to the INTOUT array.
20	PTSOUT	long	ptr to the PTSOUT array.

note: See the GEM VDI manual for a discussion of the above arrays.

24	COLBIT0	word	current color bit-plane 0 value.
26	COLBIT1	word	current color bit-plane 1 value.
28	COLBIT2	word	current color bit-plane 2 value.
30	COLBIT3	word	current color bit-plane 3 value.

note: current foreground writing color =  $1*COLBIT0 + 2*COLBIT1 + 4*COLBIT2 + 8*COLBIT3.$

32	LSTLIN	word	set this to -1 and forget it.
34	LNMASK	word	equivalent to VDI's line style.
36	WMODE	word	writing mode. (0 => replace mode, 1 => transparent mode, 2 => xor mode, 3 => inverse trans mode.)

note: see VDI manual for discussion of writing modes.

38	X1	word	x1 coordinate.
40	Y1	word	y1 coordinate.
42	X2	word	x2 coordinate.

44	Y2	word	y2 coordinate.
46	PATPTR	long	ptr to the current fill pattern.
50	PATMSK	word	fill pattern "mask".
52	MFILL	word	multi-plane fill flag. (0 => current fill pattern is single plane) (1 => current fill pattern is multi-plane)
54	CLIP	word	clipping flag (0 => no clipping)
56	XMINCL	word	minimum x clipping value.
58	YMINCL	word	minimum y clipping value.
60	XMAXCL	word	maximum x clipping value.
62	YMAXCL	word	maximum y clipping value.
64	XDDA	word	accumulator for textblt x dda.
	note:		Should be init-ed to B000H (.5) before each invocation of TextBlT.
66	DDAINC	word	fractional amount to scale up or down.
	note:		If scaling up, set DDAINC to 256*(Intended size-Actual size)/Actual size.  If scaling down, set DDAINC to 256*(Intended size)/Actual size.
68	SCALDIR	word	scale direction flag. (0 => down)
70	MONO	word	0 => current font is not monospaced OR its OK for thickening to increase the width of the current font. 1 => current font is monospaced AND thickening may not increase the width of the font.
72	SOURCEX	word	x coord of character in font form.
74	SOURCEY	word	y coord of character in font form.

note: SOURCEX can be computed from the information held in the font header. (see Appendix G of VDI manual for header def)  
e.g.  
temp = character value;  
temp -= fnt\_ptr->first\_ade;  
SOURCEX = fnt\_ptr->off\_table(temp);

SOURCEY is typically set to 0. (top line of font form)

76	DESTX	word	x coord of character on screen.
78	DESTY	word	y coord of character on screen.
80	DELX	word	width of character.
82	DELY	word	height of character.
	note:		DELX & DELY can be computed from the font header.
	e.g.		temp = character value; temp -= fnt_ptr->first_ade; SOURCEX = fnt_ptr->off_table(temp); DELX = fnt_ptr->offtable(temp+1)-SOURCEX; DELY = fnt_ptr->form_height;
84	FBASE	long	ptr to start of font data. (font form)
88	FWIDTH	word	width of font form.
	note:		FBASE & FWIDTH can be computed from the font header.
	e.g.		FBASE = fnt_ptr->dat_table; FWIDTH = fnt_ptr->form_width;
90	STYLE	word	vector of TextBlt special effects flags. Bit 0 = Thicken flag. Bit 1 = Lighten flag. Bit 2 = Skewing flag. Bit 3 = Underline flag. (ignored) Bit 4 = Outline flag.
	note:		Set the bits to select the desired effects. Underlining must be done by the application.
92	LITEMASK	word	the mask to use in lightening text.
94	SKEWMASK	word	the mask to use in skewing text.
96	WEIGHT	word	the width by which to thicken text.
98	ROFF	word	offset above character baseline when skewing.
100	LOFF	word	offset below character baseline when skewing.
	note:		The above 5 input variables can be computed from the font header.
	e.g.		LITEMASK = fnt_ptr->lighten; SKEWMASK = fnt_ptr->skew; WEIGHT = fnt_ptr->thicken; if (skewing) { ROFF = fnt_ptr->right_offset;

```

    LOFF = fnt_ptr->left_offset;
}
else {
    ROFF = 0;
    LOFF = 0;
}

```

102	SCALE	word	scaling flag. (0 => no scaling.)
104	CHUP	word	character rotation vector. 0 => normal horizontal orientation. 900 => rotated 90 degrees clockwise. 1800 => rotated 180 degrees clockwise. 2700 => rotated 270 degrees clockwise.
106	TEXTFG	word	text foreground color.
108	SCRTPHP	long	ptr to start of text special effects buffer.
112	SCRPT2	word	offset of scaling buffer in above buffer.

note: These special effects buffer pointers must be initialized before TextBlt effects can be used.

114	TEXTBG	word	text background color. (4/20/85) RAMVDI only.
116	COFYTRAN	word	copy raster form type flag. (4/26/85) RAMVDI. 0 => Opaque type n-plane source -> n-plane dest BitBlt writing modes ~0 => Transparent type 1-plane source -> n-plane dest VDI writing modes
118	SEEDABORT	long	ptr to routine which is called within the seedfill logic to allow the fill to be aborted. Initialized to point to a dummy routine which returns FALSE. Returning TRUE aborts the seedfill.

note: This ptr doesn't exist in 1st release of TOS. See Example Program #2 for the technique to use to identify the 1st TOS release.

EXAMPLE LINE "A" EQUATES

```

*
*
*
VPLANES          equ          0
VWRAP            equ          2
CONTRL           equ          4
INTIN            equ          8
PTSIN            equ         12
INTOUT           equ         16
FTSOUT           equ         20
COLBIT0          equ         24
COLBIT1          equ         26
COLBIT2          equ         28
COLBIT3          equ         30
LSTLIN           equ         32
LNMASK           equ         34
WMODE            equ         36
X1               equ          38
Y1               equ          40
X2               equ          42
Y2               equ          44
PATPTR           equ          46
PATMSK           equ          50
MFILL            equ          52
CLIP             equ          54
XMINCL           equ          56
YMINCL           equ          58
XMAXCL           equ          60
YMAXCL           equ          62
XDDA             equ          64
DDAINC           equ          66
SCALDIR          equ          68
MONO             equ          70
SRCX             equ          72
SRCY             equ          74
DSTX             equ          76
DSTY             equ          78
DELX             equ          80
DELY             equ          82
FBASE            equ          84
FWIDTH           equ          88
STYLE            equ          90
LITEMSK          equ          92
SKEWMSK          equ          94
WEIGHT           equ          96
ROFF             equ          98
LOFF             equ         100
SCALE            equ         102
CHUP             equ         104
TEXTFG           equ         106
SCRTPHP          equ         108

```



```

SCRPT2          equ          112
TEXTBG          equ          114
COPYTRAN        equ          116
SEEDABORT       equ          118
*
*
*
INIT            equ          $A000
PUTPIX          equ          INIT+1
GETPIX          equ          INIT+2
ABLINE          equ          INIT+3
HABLINE         equ          INIT+4
RECTFILL        equ          INIT+5
POLYFILL        equ          INIT+6
BITBLT          equ          INIT+7
TEXTBLT         equ          INIT+8
SHOWCUR         equ          INIT+9
HIDECUR         equ          INIT+10
CHGCUR          equ          INIT+11
DRSPRITE        equ          INIT+12
UNSPRITE        equ          INIT+13
COPYRSTR        equ          INIT+14
SEEDFILL        equ          INIT+15

```

EXAMPLE PROGRAM #1

```

text
start:          dc.w          INIT                ; initialize.
                move.w        #-1,LSTLIN(a0)      ; once and for
                ; all.
                move.w        #$5555,LNMASK(a0)    ; dithered line.
                move.w        #0,WMODE(a0)         ; replace mode.
                move.w        #1,COLBIT0(a0)
                move.w        #1,COLBIT1(a0)
                move.w        #1,COLBIT2(a0)
                move.w        #0,COLBIT3(a0)       ; drawing color
                ; = 7.
                move.w        #0,X1(a0)           ; X1 = 0.
                move.w        #0,Y1(a0)           ; Y1 = 0.
                move.w        #99,X2(a0)          ; X2 = 99.
                move.w        #99,Y2(a0)          ; Y2 = 99.
                dc.w          ABLINE               ; draw line.
                .
                .
                .
                move.w        #0,-(sp)
                trap          #1                   ; exit.
end

```

EXAMPLE PROGRAM #2

```

text
*
*
*
start:   clr.l      -(sp)
         move.w    ##20,-(sp)
         trap      #1                ; supervisor mode required
                                         ; to use line "A"
                                         ; routines via jsr.

         addq     #6,sp
         move.l   d0,stksave        ; save old stack ptr.
*
*   Find out which version of LINE "A" handler exists.
*
         move.l   #0,a2              ; convenient value for
                                         ; testing.
         dc.w     INIT              ; line "A"
                                         ; initialization.
         move.l   a2,d2              ; old version?
         bne     a2ok                ; no, a2 points to array
                                         ; of line "A" routine
                                         ; addresses.
         lea     -4*15(a1),a2        ; yes, a2 is untouched, so
                                         ; use a1 plus
                                         ; displacement (15
                                         ; addresses).
*
*   a2 now points to array of line "A" routine addresses.
*
a2ok:   move.l   4*#D(a2),drawaddr ; fetch draw
                                         ; routine address.
*
*   Bug-workaround/Initialization complete.
*
         move.w   #0,d0              ; init x.
         move.w   #0,d1              ; init y.
         lea     sprite,a0          ; point to sprite.
         lea     save,a2            ; point to save area.
*
loop:   movem.w  d0-d1,-(sp)         ; save x,y.
         movem.l a0/a2,-(sp)        ; save ptrs.
         move.l   a6,-(sp)          ; draw clobbers a6.
         tst.w   old_linea          ; old or new line "A" handler?
         beq     new                ; new, branch.
         move.l   drawaddr,a3       ; fetch draw routine
                                         ; address.
         jsr     (a3)                ; draw the old way.
         bra     merge
*
new:    dc.w     DRSPRITE            ; draw the new way.
*
merge:  move.l   (sp)+,a6

```

```

*          movem.l    (sp)+,a0/a2          ; restore ptrs.
*
wait:      move.w     #2000,d2
*          dbra       d2,wait             ; wait a bit.
*
          movem.l    a0/a2,-(sp)         ; save ptrs.
          move.l     a6,-(sp)           ; undraw clobbers a6.
          dc.w       UNSPRITE
          move.l     (sp)+,a6
          movem.l    (sp)+,a0/a2         ; restore ptrs.
          movem.w    (sp)+,d0-d1         ; restore x,y.
          addq.w     #1,d0               ; inc x.
          cmp.w      #640,d0
          ble        loop
*
          move.l     stksave,-(sp)
          move.w     ##20,-(sp)
          trap       #1                  ; user mode.
          addq      #6,sp
*
          move.w     #0,-(sp)
          trap       #1                  ; exit.
*
          data
*
*
*
sprite:   dc.w       0,0                 ; x,y offsets of hotspot.
          dc.w       1,0,1             ; format, background,
          ; foreground.
bob:      dc.w       $FFFF              ; background line 0.
          dc.w       $07F0             ; foreground line 0.
          dc.w       $FFFF
          dc.w       $0ff8
          dc.w       $FFFF
          dc.w       $1fec
          dc.w       $FFFF
          dc.w       $1804
          dc.w       $FFFF
          dc.w       $1804
          dc.w       $FFFF
          dc.w       $1004
          dc.w       $FFFF
          dc.w       $1e3c
          dc.w       $FFFF
          dc.w       $1754
          dc.w       $FFFF
          dc.w       $1104
          dc.w       $FFFF
          dc.w       $0b28
          dc.w       $FFFF
          dc.w       $0dd8
          dc.w       $FFFF
          dc.w       $0628

```

```
dc.w      $FFFF
dc.w      #07d0
dc.w      $FFFF
dc.w      #2e10
dc.w      $FFFF
dc.w      #39e0
dc.w      $FFFF
dc.w      #3800
```

```
bss
```

```
*
*
*
```

```
stksave:      ds.l      1
save:         ds.b      10+64
old_linea:    ds.w      1
drawaddr:     ds.l      1
end
```

## B

BAG 'O TRICKS, 10  
 BG COL, 6, 9, 10, 11, 12  
 BitBit, 1, 5, 12, 15, 19, 21

## C

CHUP, 12, 19, 20  
 CLIP, 4, 5, 17, 20  
 COLBIT0, 3, 4, 5, 16, 20, 21  
 COLBIT1, 3, 4, 5, 16, 20, 21  
 COLBIT2, 3, 4, 5, 16, 20, 21  
 COLBIT3, 3, 4, 5, 16, 20, 21  
 CONTRL, 2, 5, 15, 16, 20  
 Copy raster form, 1, 15, 19  
 COPYTRAN, 15, 19, 21

## D

D FORM, 6, 8  
 D NXLN, 6, 8  
 D NXPL, 6, 8  
 D NXWD, 6, 8  
 D XMIN, 6, 8  
 D YMIN, 6, 8  
 DDAINC, 12, 17, 20  
 DELX, 12, 18, 20  
 DELY, 12, 18, 20  
 DESTX, 12, 18  
 DESTY, 12, 18  
 Draw sprite, 1, 14

## E

EQUATES, 20  
 EXAMPLE PROGRAM #1, 21  
 EXAMPLE PROGRAM #2, 2, 15, 19, 22

## F

FBASE, 12, 18, 20  
 FB COL, 6, 9, 10, 11, 12  
 Filled rectangle, 1, 4, 11  
 FWIDTH, 12, 18, 20

## G

Get pixel, 1, 3

## H

Hide mouse, 1, 13  
 Horizontal line, 1, 4

I

Initialization, 1, 15, 22

L

Line, 1, 2, 3, 4, 5, 6, 7, 14, 15, 16, 18, 20, 21, 22, 23  
Line-by-line filled polygon, 1, 5  
LITEMASK, 12, 18  
LNMASK, 3, 4, 16, 20, 21  
LOFF, 12, 18, 19, 20

M

MEMORY FORMS, 8  
MFILL, 4, 5, 17, 20  
MONO, 12, 17, 20

O

OP TAB, 6, 7, 9, 10, 11, 12

P

P ADDR, 6, 9  
P BLOCK LEN  
P MASK, 6, 10  
P NXLN, 6, 9, 10  
P NXPL, 6, 10  
PARAMETER BLOCK, 6, 7  
PATMSK, 4, 5, 17, 20  
PATPTR, 4, 5, 17, 20  
PATTERNS, 1, 9  
PLANE CT, 6, 8  
PTSIN, 2, 3, 5, 16, 20  
Put pixel, 1, 2

R

RASTER OPERATIONS, 9  
ROFF, 12, 18, 19, 20

S

S FORM, 6, 8, 11, 13  
S NXLN, 6, 8, 11  
S NXPL, 6, 8, 10, 11  
S NXWD, 6, 8, 11  
S XMIN, 6, 8, 11  
S YMIN, 6, 8, 11  
SCALDIR, 12, 17, 20  
SCALE, 12, 17, 19, 20  
SCRIPT2, 13, 19, 21

SCRTCHP, 12, 19, 20  
 SEEDABORT, 19, 21  
 Seedfill, 1, 19, 21  
 Show mouse, 1, 13  
 SKEWMASK, 12, 18  
 SOURCEX, 12, 17, 18  
 SOURCEY, 12, 17, 18  
 start, 6, 8, 12, 18, 19, 21, 22  
 stksave, 22, 23, 24  
 STYLE, 3, 12, 16, 18, 20

T

TEXTBG, 12, 19, 21  
 TextBlt, 1, 12, 17, 18, 19, 21  
 TEXTFG, 12, 19, 20  
 TOS, 1, 2, 15, 19  
 Transform mouse, 1, 13

U

Undraw sprite, 1, 13

V

VDI, 1, 2, 4, 7, 8, 12, 13, 14, 15, 16, 17, 19

W

WEIGHT, 12, 18, 20  
 WMODE, 3, 4, 5, 12, 16, 20, 21

X

XDDA, 12, 17, 20  
 XMAXCL, 5, 17, 20  
 XMINCL, 4, 5, 17, 20

Y

YMAXCL, 5, 17, 20  
 YMINCL, 5, 17, 20

